



How To: Connections on the Morimoto Single Xenon Relay Harness

Warning: By reading this document I agree that it is only intended to be used as an educational guide. The Retrofit Source Inc. makes no guarantee on any finished results, nor are they to be held responsible for any damage, misuse, or personal injuries. Use at your own risk. If you are unable to clearly understand and adapt the information contained below to your own application, professional installation is available and recommended.

Time Required: 5-15 minutes

Parts Used: Morimoto H7 Bi-xenon Relay Harness

Connections:

- 1) **Harness Input:** Plugs into the output socket which used to plug into your halogen bulb on the side closest to the car battery
- 2) **Battery (+):** Coming from the fuse box with the red wire, goes to the positive battery terminal or any 12v output
- 3) **Ground (-):** Coming from the black line, you can connect this to the battery or any chassis ground
- 4) **Ballast Outputs:** Comes from the orange/black color coded wires. Longer side plugs into ballast opposite battery

Note: Depending on your model, the "Harness Input" socket may look different.

